

In Windows

Start > Programs > Accessories > Communications > HyperTerminal

Set Up a HyperTerminal

Assign Any Name and Icon

Connect Using: TCP/IP (winsock)

Address: 192.168.0.1

Port: 1953

Wait a few seconds and for the console to appear.

Menu Options:

To display the menu options hit enter

Display Active Routing Table:

Menu option (d) displays the current data in the Active Routing Table

Reset History:

Menu option (h) displays the reset history for the DW modem.

To Reset the Modem (Rebooting):

You can reset the DW modem by typing “**rr**” at the Main Menu prompt and pressing Enter. You can force the DW modem to download new keys and new software by typing “**rd**” and pressing Enter.

Note: You will not see any key command that you type.

For Use of wiping out current software, and starting over.

Using TelNet

Start > Run > Type “cmd” and then hit enter

Type “telnet 192.168.0.1 1953” then hit enter

Wait for the window to load. Note: You will not see the letters you type from this point.

Type “ rf ” then hit enter.

The modem will restart, and come back on with a flashing Power and LAN light.